

Honda EU2000i- 1600 Watt Portable Inverter

Model:EU2000T1A1

Run Watts

1,600Rated Watts

Surge Watts

2,000Starting Watts



Product Specs

Voltage 120Single-Phase

Frequency 60 Hertz

Alternator Inverter

Auto Voltage Regulation Yes

Rated Watts 1600 Watts

Surge Watts 2000 Watts

Fuel Type Gasoline

Rated Amps 13Amps

Portability Kit Sold Separately

Tank Size 0.95 Gallons

Fuel Tank Material Plastic

Fuel Gauge No

Idle Control Yes

Hour Meter No

Voltage Meter No

Lifting Eye No

Battery NotApplicable

Grade Type Recreational

Engine

Engine Brand HondaGX

Starting System Recoil Start

Low OilAlert/Shutdown Yes

46.3Pounds

20.1Inches

11.4Inches

16.7Inches